

13 Technical data of the motors

INFORMATION



You find more information in the "AC Motors" catalog.

13.1 Key to the data tables

The following table lists the short symbols used in the "Technical data" tables.

P_N	Rated power
M_N	Rated torque
n_N	Rated speed
I_N	Rated current
$\cos\varphi$	Power factor
$\eta_{50\%}$	Efficiency at 50% of the rated power
$\eta_{75\%}$	Efficiency at 75% of the rated power
$\eta_{100\%}$	Efficiency at 100% of the rated power
I_A/I_N	Starting current ratio
M_A/M_N	Starting torque ratio
M_H/M_N	Ramp-up torque ratio
M_K/M_N	Breakdown torque ratio
m_{Mot}	Mass of the motor
J_{Mot}	Mass moment of inertia of the motor
BE..	Brake used
Z_0 BG	Switching frequency for operation with BG brake controller
Z_0 BGE	Switching frequency for operation with BGE brake controller
M_B	Braking torque
m_{BMot}	Mass of the brakemotor
J_{BMot}	Mass moment of inertia of the brakemotor

13.2 IE1 DR2S.. motors. 400 V, 50 Hz, 4-pole

13.2.1 Information on motors

DR2S.. motor type	P _N kW	M _N Nm	n _N min ⁻¹	I _N 400 V A	cosφ	η _{50%} %	η _{75%} %	η _{100%} %	I _A /I _N	M _A /M _N M _H /M _N	M _K /M _N
DR2S56MR4 ¹⁾	0.09	0.62	1380	0.35	0.61	43.9	51.4	54.8	3.0	2.8 2.8	2.9

1) DR2S56.. motors will be available in spring 2019.

13.2.2 Further information for motors and brakemotors

DR2S.. motor type	P _N kW	M _N Nm	n _N min ⁻¹	m _{Mot} kg	J _{Mot} 10 ⁻⁴ kgm ²	BE..	Z ₀ BG BGE h ⁻¹	M _B Nm	m _{BMot} kg	J _{BMot} 10 ⁻⁴ kgm ²
DR2S56MR4 ¹⁾	0.09	0.62	1380	²⁾	1.2	BE02	10000 -	0.8	²⁾	1.3

1) DR2S56.. motors will be available in spring 2019.

2) Only available as gearmotor

13.3 IE3 DRN.. motors, 400 V, 50 Hz, 2-pole

13.3.1 Information for motors

Motor	P _N kW	M _N Nm	n _N min ⁻¹	I _N A	cosφ	η _{50%} %	η _{75%} %	η _{100%} %	I _A /I _N	M _A /M _N M _H /M _N	M _K /M _N
DRN63MS2	0.18	0.63	2725	0.465	0.78	62.7	66.2	65.9	4.2	2.6 2.6	2.6
DRN63M2	0.25	0.87	2755	0.57	0.81	69.2	70.9	69.7	4.9	2.7 2.6	2.7
DRN71MS2	0.37	1.26	2810	0.87	0.78	70.7	73.8	73.8	5.4	3.1 2.7	3.1
DRN71M2	0.55	1.86	2825	1.24	0.81	75.7	78.0	77.8	5.9	3.2 3.0	3.2
DRN80MS2	0.75	2.5	2855	1.58	0.84	80.2	82.0	81.4	5.9	2.8 2.5	2.9
DRN80M2	1.1	3.65	2860	2.2	0.85	83.1	84.1	83.0	6.6	3.0 2.5	2.9
DRN90S2	1.5	4.95	2886	3.1	0.83	83.7	85.0	84.2	6.6	2.7 2.5	2.9
DRN90L2	2.2	7.2	2905	4.3	0.85	86.1	86.7	85.9	7.4	2.5 2.1	3.0
DRN100LM2	3	9.9	2894	5.8	0.85	88.9	88.7	87.2	7.7	3.3 2.6	3.5
DRN112M2	4	13	2948	7.5	0.86	88.1	88.7	88.1	10.6	2.9 1.3	3.3
DRN132S2	5.5	17.9	2935	9.4	0.92	90.3	90.2	89.2	10.0	3.0 2.1	3.7
DRN132S2	7.5	24.5	2936	14.1	0.85	90.6	90.8	90.1	9.6	3.3 2.0	3.4

13.3.2 Further information for motors and brakemotors

Motor	P _N kW	M _N Nm	n _N min ⁻¹	m _{Mot} kg	J _{Mot} 10 ⁻⁴ kgm ²	BE..	Z ₀ BG BGE h ⁻¹	M _B Nm	m _{BMot} kg	J _{BMot} 10 ⁻⁴ kgm ²
DRN63MS2	0.18	0.63	2725	4.9	2.95	BE03	5000 6000	1.3	6.8	3.63
DRN63M2	0.25	0.87	2755	5.8	3.76	BE03	4500 6000	1.7	7.6	4.44
DRN71MS2	0.37	1.26	2810	6.8	2.93	BE03	6000 3600	2.7	8.6	3.61
DRN71M2	0.55	1.86	2825	8	3.71	BE05	2600 5500	5	10	5.01
DRN80MS2	0.75	2.5	2855	11	18.5	BE05	1200 3400	5	15	20
DRN80M2	1.1	3.65	2860	14	24.1	BE1	1000 2600	7	18	25.6
DRN90S2	1.5	4.95	2886	20	53.1	BE1	600 1300	10	22	54.7
DRN90L2	2.2	7.2	2905	23	66.3	BE2	- 1000	14	27	71
DRN100LM2	3	9.9	2894	33	89.7	BE2	- 750	20	37	94.4
DRN112M2	4	13	2948	45	178	BE5	- 400	28	52	183
DRN132S2	5.5	17.9	2935	56	241	BE5	- 300	40	64	246
DRN132S2	7.5	24.5	2936	56	241	BE5	- 300	55	64	246

13.4 IE3 DRN.. motors, 400 V, 50 Hz, 4-pole

13.4.1 Information on motors

Motor	P _N kW	M _N Nm	n _N min ⁻¹	I _N A	cosφ	η _{50%} %	η _{75%} %	η _{100%} %	I _A /I _N	M _A /M _N M _H /M _N	M _K /M _N
DRN63MS4	0.12	0.83	1380	0.4	0.64	58.3	63.9	64.8	3.6	2.7 2.6	2.7
DRN63M4	0.18	1.25	1375	0.57	0.65	65.1	69.4	69.9	3.7	2.6 2.6	2.6
DRN71MS4	0.25	1.7	1405	0.72	0.66	70.1	73.5	73.5	4.3	2.5 2.3	2.5
DRN71M4	0.37	2.5	1415	1.02	0.66	74.3	77.3	77.3	4.8	2.8 2.4	2.8
DRN80MK4	0.55	3.65	1435	1.29	0.75	78.6	81.0	80.8	6.1	2.7 2.1	3.1
DRN80M4	0.75	4.95	1440	1.75	0.74	80.7	82.9	82.9	6.7	3.1 2.7	3.4
DRN90S4	1.1	7.2	1455	2.55	0.73	83.5	85.0	84.5	6.9	2.7 2.1	3.3
DRN90L4	1.5	9.8	1461	3.4	0.74	84.6	86.1	85.6	7.5	2.7 2.0	3.3
DRN100LS4	2.2	14.5	1450	4.75	0.76	86.4	87.5	86.9	7.1	2.9 2.2	3.3
DRN100L4	3	19.7	1456	6.4	0.76	87.3	88.3	87.8	8.2	3.4 2.3	3.7
DRN112M4	4	26	1464	7.9	0.81	88.6	89.4	88.7	8.2	2.4 1.6	3.6
DRN132S4	5.5	36	1461	10.5	0.84	90.6	90.6	89.6	8.3	2.8 2.2	3.5
DRN132M4	7.5	49	1468	15.2	0.78	90.8	91.1	90.4	7.8	3.1 2.4	3.3
DRN132L4	9.2	60	1470	18.7	0.77	90.8	91.6	91.0	8.4	3.7 1.8	3.7
DRN160M4	11	71	1473	21	0.81	91.1	91.7	91.4	7.3	2.6 2.2	3.0
DRN160L4	15	97	1474	29	0.80	91.9	92.5	92.1	8.0	3.0 2.0	3.4
DRN180M4	18.5	120	1478	33.5	0.85	92.8	93.1	92.6	9.5	3.6 2.9	3.6
DRN180L4	22	142	1477	38.5	0.87	93.4	93.6	93.0	9.6	3.5 2.1	3.4
DRN200L4	30	194	1480	56	0.82	93.3	93.9	93.6	8.2	2.9 2.5	3.3
DRN225S4	37	240	1482	64	0.88	94.3	94.4	93.9	8.4	3.0 2.3	2.7
DRN225M4	45	290	1482	81	0.85	94.1	94.5	94.2	8.8	3.0 2.2	2.7
DRN250M4	55	355	1482	104	0.80	94.4	94.8	94.6	8.2	4.0 2.5	2.9
DRN280S4	75	485	1482	143	0.79	94.9	95.3	95.0	7.6	3.7 2.6	2.9
DRN280M4	90	580	1481	161	0.84	95.4	95.6	95.2	7.7	3.6 2.0	2.7
DRN315S4	110	710	1488	189	0.87	95.4	95.7	95.5	6.7	2.9 2.1	3.1
DRN315M4	132	850	1487	230	0.87	95.6	95.9	95.6	6.5	2.7 2.0	2.9
DRN315L4	160	1030	1486	275	0.87	95.9	96.1	95.9	6.5	2.7 2.0	2.8
DRN315H4	200	1280	1489	355	0.84	95.4	96.0	96.0	8.1	3.7 2.8	3.8

13.4.2 Further information on motors and brakemotors

Motor	P _N kW	M _N Nm	n _N min ⁻¹	m _{Mot} kg	J _{Mot} 10 ⁻⁴ kgm ²	BE..	Z ₀ BG BGE h ⁻¹	M _B Nm	m _{BMot} kg	J _{BMot} 10 ⁻⁴ kgm ²
DRN63MS4	0.12	0.83	1380	4.9	2.95	BE03	10000 10000	1.7	6.8	3.63
DRN63M4	0.18	1.25	1375	5.8	3.76	BE03	10000 10000	2.7	7.6	4.44
DRN71MS4	0.25	1.7	1405	6.8	5.42	BE03	6200 9700	3.4	8.6	6.11
DRN71M4	0.37	2.5	1415	8	7.14	BE05	5000 9000	5	10	8.44
DRN80MK4	0.55	3.65	1435	11	17.1	BE1	3500 8500	7	14	18.6
DRN80M4	0.75	4.95	1440	14	24.7	BE1	3200 8200	10	18	26.2
DRN90S4	1.1	7.2	1455	20	54	BE2	2300 6000	14	24	58.7
DRN90L4	1.5	9.8	1461	23	67.2	BE2	2200 5800	20	27	71.9
DRN100LS4	2.2	14.5	1450	27	81.4	BE5	- 6100	28	33	87.4
DRN100L4	3	19.7	1456	34	112	BE5	- 3700	40	40	118
DRN112M4	4	26	1464	45	178	BE5	- 2900	55	52	183
DRN132S4	5.5	36	1461	56	241	BE11	- 2100	80	71	251
DRN132M4	7.5	49	1468	73	381	BE11	- 1100	110	91	403
DRN132L4	9.2	60	1470	81	439	BE20	- 980	150	110	490
DRN160M4	11	71	1473	115	817	BE20	- 900	150	145	877
DRN160L4	15	97	1474	130	1040	BE20	- 800	200	165	1100
DRN180M4	18.5	120	1478	155	1630	BE30	- 510	300	195	1770
DRN180L4	22	142	1477	170	1950	BE30	- 470	300	210	2090
DRN200L4	30	194	1480	280	2660	BE32	- 500	400	335	2890
DRN225S4	37	240	1482	310	4350	BE32	- 230	500	365	4580
DRN225M4	45	290	1482	310	4350	BE32	- 200	600	365	4580
DRN250M4	55	355	1482	460	7360	BE62	- 180	800	550	7960
DRN280S4	75	485	1482	520	8940	BE62	- 150	1000	600	9530
DRN280M4	90	580	1481	630	12000	BE62	- 79	1200	720	12600
DRN315S4	110	710	1488	870	23400	BE122	- 53	1600	1000	24400
DRN315M4	132	850	1487	890	24800	BE122	- 46	2000	1020	25800
DRN315L4	160	1030	1486	1020	28600	BE122	- 34	2000	1150	29600
DRN315H4	200	1280	1489	1130	35200	BE122	- 23	2000	1270	36200

24832936/EN – 09/2018

13.5 IE3 DRN.. motors, 400 V, 50 Hz, 6-pole

13.5.1 Information for motors

Motor	P _N kW	M _N Nm	n _N min ⁻¹	I _N A	cosφ	η _{50%} %	η _{75%} %	η _{100%} %	I _A /I _N	M _A /M _N M _H /M _N	M _K /M _N
DRN63MR6	0.09	0.93	920	0.36	0.58	44.3	51.7	55.0	2.9	2.7 2.6	2.8
DRN63M6	0.12	1.32	870	0.4	0.71	51.9	57.5	57.7	2.6	1.9 1.8	1.9
DRN71MS6	0.18	1.88	915	0.55	0.69	59.4	63.7	63.9	3.4	1.9 1.9	2.2
DRN71M6	0.25	2.6	915	0.76	0.68	63.5	68.2	68.6	3.4	2.0 1.9	2.3
DRN80MK6	0.37	3.8	935	1.05	0.68	70.8	73.8	73.5	4.1	2.1 2.1	2.4
DRN90SR6	0.55	5.4	966	1.52	0.65	73.5	76.7	77.2	5.2	2.3 2.2	2.8
DRN90S6	0.75	7.5	957	2	0.68	77.4	79.8	78.9	4.8	2.0 2.0	2.4
DRN90L6	1.1	11	957	2.95	0.67	78.8	81.3	81.0	5.0	2.4 2.3	2.8
DRN100L6	1.5	14.9	961	4.1	0.63	80.7	82.8	82.5	4.7	2.2 2.2	2.9
DRN112M6	2.2	21.5	973	5.5	0.66	83.6	85.0	84.3	6.5	2.4 1.9	3.2
DRN132S6	3	29.5	974	7.4	0.66	84.8	86.0	85.6	6.2	2.6 2.5	3.4
DRN132S6	4	39.5	968	9.7	0.68	86.4	87.5	86.8	5.5	2.5 2.5	3.2
DRN132L6	5.5	54	975	13.8	0.64	86.9	88.3	88.0	5.6	2.7 2.5	2.8
DRN160M6	7.5	73	979	15.8	0.74	88.4	89.4	89.1	8.2	2.7 1.6	4.0

13.5.2 Further information for motors and brakemotors

Motor	P _N kW	M _N Nm	n _N min ⁻¹	m _{Mot} kg	J _{Mot} 10 ⁻⁴ kgm ²	BE..	Z ₀ BG BGE h ⁻¹	M _B Nm	m _{BMot} kg	J _{BMot} 10 ⁻⁴ kgm ²
DRN63MR6	0.09	0.93	920	5.8	6.47	BE03	12000 12000	2.1	7.6	7.16
DRN63M6	0.12	1.32	870	5.8	6.47	BE03	12000 12000	2.7	7.6	7.16
DRN71MS6	0.18	1.88	915	6.8	8.29	BE05	7000 12000	5	9.2	9.59
DRN71M6	0.25	2.6	915	8	10.4	BE05	5200 12000	5	10	11.7
DRN80MK6	0.37	3.8	935	11	17.1	BE1	3000 9000	10	14	18.6
DRN90SR6	0.55	5.4	966	20	54	BE2	2400 5000	14	24	58.7
DRN90S6	0.75	7.5	957	20	54	BE2	2400 5000	20	24	58.7
DRN90L6	1.1	11	957	23	67.4	BE5	2200 4400	28	29	73.4
DRN100L6	1.5	14.9	961	34	112	BE5	- 3400	40	40	118
DRN112M6	2.2	21.5	973	45	178	BE5	- 2500	55	52	183
DRN132S6	3	29.5	974	56	245	BE11	- 2300	80	71	256
DRN132S6	4	39.5	968	56	245	BE11	- 2100	80	71	256
DRN132L6	5.5	54	975	81	439	BE11	- 1700	110	100	461
DRN160M6	7.5	73	979	115	1290	BE20	- 1200	150	145	1350

13.6 IE3 DRN.. motors, 400 V, 50 Hz, 8-pole

13.6.1 Information on motors

DRN.. motor type	P _N kW	M _N Nm	n _N min ⁻¹	I _N A	cosφ	η _{50%} %	η _{75%} %	η _{100%} %	I _A /I _N	M _A /M _N M _H /M _N	M _K /M _N
DRN71MSR8	0.09	1.24	695	0.435	0.53	39.0	46.7	50.7	2.4	2.3 2.3	2.6
DRN71MS8	0.12	1.72	665	0.47	0.64	46.2	52.4	53.5	2.3	1.6 1.6	1.8
DRN80MK8	0.18	2.45	705	0.76	0.54	49.4	56.1	58.7	3.0	1.8 1.8	2.4
DRN80M8	0.25	3.4	702	1.02	0.53	55.8	62.0	64.1	3.1	2.0 1.9	2.3

13.6.2 Further information on motors and brakemotors

DRN.. motor type	P _N kW	M _N Nm	n _N min ⁻¹	m _{Mot} kg	J _{Mot} 10 ⁻⁴ kgm ²	BE..	Z ₀ BG BGE h ⁻¹	M _B Nm	m _{BMot} kg	J _{BMot} 10 ⁻⁴ kgm ²
DRN71MSR8	0.09	1.24	695	6.8	8.29	BE03	6000 16000	2.7	8.6	8.98
DRN71MS8	0.12	1.72	665	6.8	8.29	BE03	6000 16000	3.4	8.6	8.98
DRN80MK8	0.18	2.45	705	11	17.1	BE05	5000 11500	5	14	18.6
DRN80M8	0.25	3.4	702	14	24.7	BE1	3700 10500	7	18	26.2